


DC to AC POWER INVERTER

NEDA-0350AH-12
NEDA-0350AH-24



Model No.	NEDA-0350AH-12	NEDA-0350AH-24
Output power continuous	350W	350W
Instant Surge	700W	700W
AC Output Voltage	100V/110V/115/120VAC 220V/230V/240VAC	100V/110V/115/120VAC 220V/230V/240VAC
Regulation	± 5%	± 5%
DC Input Voltage	10V~15VDC	20~30VDC
Output frequency	50Hz or 60Hz ± 3%	50Hz or 60Hz ± 3%
Low Battery Alarm	10.5V ± 0.5V	21V ± 0.8V
Low Battery Shut-Down	10V ± 0.5V	20V ± 0.8V
Standby Current	<0.25A	<0.2A
Efficiency	>85%	>85%
Thermal Protect	50°C ± 5°C	50°C ± 5°C
Cooling	Auto Temperature Control Fan	Auto Temperature Control Fan
Protections	Output Short Shutdown Battery Low Alarm/Shutdown Input Polarity Reverse (By fuse) High/Low Voltage Input Shutdown Over Load Shutdown Over Temperature Shutdown AVR Design Input/Output Isolated	Output Short Shutdown Battery Low Alarm/Shutdown Input Polarity Reverse (By fuse) High/Low Voltage Input Shutdown Over Load Shutdown Over Temperature Shutdown AVR Design Input/Output Isolated
Fuse	Battery Cord 35A X 1pc Cigarette Plug 15A X 1pc	Battery Cord 20A X 1pc Cigarette Plug 10A X 1pc
AC Outlet	Cigar Plug & Clip	Cigar Plug & Clip
Dimensions(L x W x H)	190 * 90 * 75 mm	190 * 90 * 75 mm
Net weight (by Kg/s)	1	1
Output Waveform	 Modified sine wave	 Modified sine wave