



## LED-BLITZLEUCHE SOLISTA | LED-BEACON SOLISTA

- Sehr geringe Stromaufnahme  
- Ultra low current consumption
- Hohe Zuverlässigkeit  
- High reliability
- Einzelgerät oder als Blitz- und Soundkombination  
- Stand alone or integrated formats
- Passend für Universalsockel S-, D- und U-Base  
- Shallow-, Deep- and U-Base compatible
- Kompakte Bauform  
- Compact size

- Die neue Solista, sehr geringe Stromaufnahme aufgrund neuer LED-Technologie. Kombinierbar mit den Sirenen ROLP (Roshni Low Profile) und Squashni oder als Einzelgerät einsetzbar.
- New Solista - a LED Beacon of ultra low current consumption. To be combined with ROLP (Roshni Low Profile) and Squashni or to be used as stand-alone Beacon.

### SPEZIFIKATIONEN / SPECIFICATIONS

MODEL	Solista Beacon (stand - alone beacon)**
OPERATING VOLTAGE	9 - 28VDC*
CURRENT CONSUMPTION	3mA / 6mA at 24VDC User selectable
FLASH RATE	0.5Hz/1Hz User selectable
FLASH INTENSITY	> 0.5Cd at 3mA > 1.0Cd at 6mA
OPERATING TEMPERATURE	-10°C to + 55°C
LINE MONITORING	Reverse polarity
IP RATING	Shallow Base = IP54, Deep Base = IP65, U-Base = IP65
BASE OPTIONS	Fulleon bayonet bases, Shallow, Deep, "U"
LENS COLOUR	Red
BODY COLOUR	Red or White
WEIGHT	0.1kg
CONSTRUCTION	ABS Body / polycarbonate lens
APPROVALS	N/A

\* 110 bis 230VAC mit Powered Base / 110 to 230VAC with Powered Base  
 \*\* ACHTUNG! Die Sockel S-, D- oder U-Base müssen separat bestellt werden! / ATTENTION! Bases S-, D- or U have to be ordered separately!