

# DC to AC POWER INVERTER

NEDA-0150AH-12

NEDA-0150AH-24



**Neumüller**  
Elektronik GmbH



Model No.	NEDA-0150AH-12	NEDA-0150AH-24
Output power continuous	150W	150W
Instant Surge	300W	300W
AC Output Voltage	100V/110V/115V/120Vac or 220V/230V/240Vac	100V/110V/115V/120Vac or 220V/230V/240Vac
Regulation	±5~10%	±5~10%
DC Input Voltage	10~15V	20~30V
Low Battery Alarm & Shut-Down	10.5V±0.5VDC & 10V±0.5VDC	21V±0.8VDC & 20V±0.8VDC
Input Low Voltage Protection	Yes	Yes
Reverse Polarity Protection	Yes	Yes
Soft Start	Yes	Yes
DC/AC Isolated	Yes	Yes
AVR Design	Yes	Yes
Overload Protection	Yes	Yes
Remote Control	No	No
Temperature protection	50°C ± 5°C	50°C ± 5°C
Efficiency	>85%	>85%
No Load Current	<0.25A	<0.25A
Dimensions (L x W x H mm)	116 * 102 * 63	116 * 102 * 63
Net weight (by Kg/s)	0.7	0.7
Accessory	Cigar Plug	Cigar Plug
Output Waveform (Modified sine wave)		